## DRACAST

## LED1000 X-SERIES

suspension clamps.

DRX1000RGB

The X Series is the newest generation of LED panel lights from Dracast. The X-Series is designed with portability in mind, with each model weighing just a few pounds. The panel includes an installed mounting yoke with a 5/8" baby pin receiver for fast and easy mounting on compatible light stands or



The X Series is available in three versions: 5600K, 3200K - 5600K Variable CCT, and 2800K - 8000K Variable CCT PLUS full spectrum RGB. X-Series panels are also available in three sizes: LED500 (35W), LED1000 (70W), and LED2000 (120W). All X-Series sizes and variations are compatible with the Dracast DRX app for iOS and Android. X-Series lights feature dual NP-F battery plates for optional battery power on the go.

Also included are preset color gels and filters, as well as a collection of customizable effects and presets (RGB models). The light can be fully controlled manually via the user-friendly control panel on the back of the fixture, or by using Dracast DRX. Using the DRX companion app, all of the features of the light can be easily controlled along with the added ability to control multiple X-Series lights simultaneously.

Dracast X-Series lights include the fixture, mounting yoke, soft carry case, power adapter, and power cable. Other accessories such as barn doors, softbox, and light stands are available and sold separately.

Photometric Data	1	3 ft / 0.9 m	6 ft / 1.8 m	9 ft / 2.7 m	12 ft / 3.6 m
X-SERIES LED1000 5600K DRX1000DN		137 fc	43 fc	21 fc	13 fc
		1480 lux	464 lux	231 lux	140 lux
X-SERIES LED1000 3200K - 5600K DRX1000BN		116 fc @ 3200K	34 fc @ 3200K	17 fc @ 3200K	10 fc @ 3200K
		118 fc @ 4400K	40 fc @ 4400K	20 fc @ 4400K	12 fc @ 4400K
		131 fc @ 5600K	40 fc @ 5600K	20 fc @ 5600K	12 fc @ 5600K
		1246 lux @ 3200K	363 lux @ 3200K	185 lux @ 3200K	113 lux @ 3200K
		1275 lux @ 4400K	428 lux @ 4400K	217 lux @ 4400K	133 lux @ 4400K
		1408 lux @ 5600K	427 lux @ 5600K	217 lux @ 5600K	132 lux @ 5600K
X-SERIES LED1000 2800K - 8000K PLUS FULL SPECTRUM RGB DRX1000RGB		111 fc @ 2800K	33 fc @ 2800K	16 fc @ 2800K	10 fc @ 2800K
		128 fc @ 5600K	38 fc @ 5600K	19 fc @ 5600K	11 fc @ 5600K
		138 fc @ 8000K	41 fc @ 8000K	20 fc @ 8000K	12 fc @ 8000K
		196 lux @ 2800K	356 lux @ 2800K	177 lux @ 2800K	108 lux @ 2800k
		1375 lux @ 5600K	406 lux @ 5600K	203 lux @ 5600K	123 lux @ 5600k
		1486 lux @ 8000K	438 lux @ 8000K	219 lux @ 8000K	129 lux @ 8000k
Part No.	ncluded				
DRX1000DN L	LED1000 X-Series 5600K Light, Aluminum 5/8" Baby Pin Yoke, Nylon Clam Shell Case, 12V A/C Power Supply, NP-F Mount Battery Plate				
DRX1000BN L	LED1000 X-Series Bicolor Light, Aluminum 5/8" Baby Pin Yoke, Nylon Clam Shell Case, 12V A/C Power Supply, NP-F Mount Battery Plate				


LED1000 X-Series Bicolor + RGB Light, Aluminum 5/8" Baby Pin Yoke, Nylon Clam Shell Case, 12V A/C Power Supply, NP-F Mount Battery Plate

## DRACAST

FIXTURE WEIGHT: 3.90 LBS (1.80 KG) PACKAGED WEIGHT: 7.00 LBS (3.18 KG)







Specifications	Details			
Optical System	DRX1000DN - 256 5600K High Output SMD LED chips			
	DRX1000BN - 256 3200K + 256 5600K High Output SMD LED chips			
	DRX1000RGB - 297 3200K + 297 5600K + 288 RGB High Output SMD LED chips			
Light Aperture	17 x 8 inches (330mm x 203mm)			
Beam Angle	100 degrees			
Weight	3.90 lbs (1.80 kg)			
Handling	Aluminum Yoke, Dual Locking Tilt Control			
Mounting	Baby 5/8" Pin			
Tilt Angle	+/- 180 degrees			
Voltage Input	15V / 5A DC			
Power Consumption	70 W			
Power Connection	Barrel connector, 90 - 240 VAC, 50 - 60 Hz, 5.0 A			
Battery Connection	Dual NPF Battery Plate (included)			
Battery DC Voltage	7.4 x 2			
Battery Light Output	100% of Total Output			
Color Temperature	5600K Fixed CCT or 3200K - 5600K Variable CCT or Variable CCT + RGB			
Color Rendition	CRI > 96			
Dimming	0% - 100% Continuous			
Controls	Local On-Board Manual Controls, App Control, Group Master / Slave Control			
Housing Color	Anodized Blue / Black			
Housing Build	Aluminum / Plastic			
Est. LED Lifetime	50,000 hours			
Available Accessories				
BDDRX1000	Dracast Barndoors for X-Series 1000			
DRSBX1000	Dracast Softbox for X-Series 1000			
DRLSCLS	Dracast Compact Portable Light Stand			
DRBKNPF6000D	Dracast NP-F Battery Kit - x2 6600 mah batteries x1 digital NP-F charger			
DB0068	DCB Element 7975F Waterproof Utility Case with Foam Insert			
DRKITBAG	Dracast Nylon Padded Travel Case			

